

Standard Transformer Options

Model	Transformer Option	Line Voltage (AC)	XFMR Model	Primary Voltage (AC)	Secondary Voltage				Turns Ratio			
					Tap 1	Tap 2	Tap 3	Tap 4	Tap 1	Tap 2	Tap 3	Tap 4
RPW-1	63KVA AC	480	M48663X6060LX	480	4.0	4.8	5.7	6.8	120:1	100:1	84:1	70:1
		600	M60663X6136LX	600	4.3	5.0	5.8	6.8	138:1	118:1	102:1	88:1
	100KVA MFDC	480	TDC-1064	650	9.0	-	-	-	72:1	-	-	-
		600	TDC-5602	800	9.1	-	-	-	88:1	-	-	-
RPW-2	125KVA AC	480	M486125C6061LX	480	7.5	8.1	8.5	9.0	64:1	59:1	56:1	53:1
		600	M606125C6137LX	600	7.5	8.1	8.5	9.0	80:1	74:1	70:1	66:1
	135KVA MFDC	480	TDC-5610	650	9.0	-	-	-	72:1	-	-	-
		600	TDC-5681	800	9.1	-	-	-	88:1	-	-	-
RPW-3	200KVA AC	480	M486200DL6062LX	480	12.0	12.9	13.7	14.5	40:1	37:1	35:1	33:1
		600	M606200DL6138LX	600	12.0	13.0	13.6	14.6	50:1	46:1	44:1	41:1
	170KVA MFDC	480	TDC-1078	650	9.5	13.0	-	-	68:1	50:1	-	-
		600	TDC-5620	800	9.5	13.1	-	-	84:1	61:1	-	-

Other transformer options available. Contact WTC Sales Representative for more information.